



60kVA Silent Canopied Generator Technical Data Sheet

Generator Size kVA	Dimensions and Weights				Fuel Tank Capacity (L)	Output Ratings		Sound Pressure Levels		Fuel Consumption Estimation		
	Length (L)	Width (W)	Height (H)	Wet		Prime 400V, 50Hz, kW, 0.8PF	Maximum Amps, 400V per phase	@ 7m : dBA	@ 1m : dBA	50% Load	75% Load	100% Load
	mm(in)	mm(in)	mm(in)	kg (lb)								
60	2924 (115.1)	1230 (48.4)	1955 (76.9)	2031 (4478)	497	48	83.4	59.5	70.9	9.4	13.7	17.9

- Fork Pockets
- Battery Isolator
- 3-Way Fuel Valve
- Bunded Fuel Tank
- Inspection Hatch

Cambridge

Brook Farm, Thrapston Road,
Ellington, Huntingdon. PE28 0AE

☎ +44 (0) 1480 893 889

✉ enquiries@pe-generators.co.uk

Glasgow

65 Craigton Road, Glasgow, Scotland, G51 3EQ

☎ +44 (0) 141 309 5440

✉ enquiries@pe-generators.co.uk

PE Generators reserve the right to supply alternative size equipment. All equipment will be fit for purpose and no extra cost will apply. The above dimensions are for indicative purposes only.



POWERING EXCELLENCE

www.pe-generators.co.uk